

HARD WIRE EXIT FIXTURE RETROFIT KIT

(CONFORMS TO UL924)

INSTALLATION INSTRUCTIONS

Save These Instructions for Important Safeguards

When installing electrical equipment, safety precautions

Should always be followed including the following:

Please Read the Following Safety Instructions

- 1 Do not use outdoors.
- 2 Do not use this equipment for other than its intended use.
- 3 Do not mount near gas or electric heaters.
- 4 Equipment should be installed where tampering by unauthorized persons would be minimized.
- 5 Servicing of this equipment should be done by qualified personnel only.

Installation Instructions for 120 V/AC and 277 V/AC

1. Disconnect branch circuit power.
2. Install this device in accordance with national, state, and local safety codes.
3. All wiring connections must be made in the wiring compartment/junction box. You may need to dismount the exit fixture to access the junction box.
4. Open exit fixture and/or remove face plates, etc.
5. Mount the unit arrays into the mounting brackets. This is accomplished by sliding the neck of the arrays into the mounting brackets. See Illustration for proper orientation.
6. Slide the mounting bracket support into the ends of the channel at the height position which provides the best illumination. The arrays mounting brackets can also be adjusted to optimize even illumination by sliding the brackets left or right. Test this position by pre-positioning the assembly before doing step # 7.
7. Peel off the paper backing from the double stick tape mounted on the bottom of the mounting Bracket support. Mount the assembly to the fixture.
8. FOR 120 VOLT WIRING: (In Parallel)
Connect both white lead wires to the neutral (white) supply wire and both black lead wires to the live (black) supply wire.
9. FOR 277 VOLT WIRING: (In Series)
Connect the white lead wire from the left array and the black lead wire from the right array together. Connect the remaining white lead wire to the neutral (white) supply lead. Connect the remaining black lead wire to the live (black) supply lead.
10. Position the wiring for minimal interference with the light from the LED arrays.
11. Remount the exit fixture, if necessary. Install the face plates, etc. and close exit fixture. Reconnect the branch circuit power.

DO NOT REMOVE THIS LABEL UNTIL READY FOR INSTALLATION IMPORTANT SAFEGUARDS-READ AND FOLLOW THESE INSTRUCTIONS BEFORE INSTALLING.

- For use only with the exit light parameter specified in the installation instructions.
- For use in exit lights with interior enclosure dimensions of 6-1/4" H × 9-1/2" W × 7/8" D minimum and 8-7/8" H × 13-7/16" W × 3-1/4" D maximum, including all obstructions.
- For use in metal enclosure only, Not for use in recessed enclosures, The current rating of the kit multiplied by the voltage rating of the kit shall not exceed the total wattage of the lamps replaced.
- Remove DC lampholders from exit light prior to installation.

CAUTION: See instruction manual for installation, operation and maintenance instructions.