

EXIT FIXTURE RETROFIT KIT (MODEL: RFXTE-3)  
120 VAC 1.4W WATTS (EACH) MAXIMUM  
(CONFORMS TO UL924)

SAVE THESE INSTRUCTIONS

**IMPORTANT SAFEGUARDS-READ AND FOLLOW ALL SAFETY INSTRUCTIONS**

When installing electrical equipment, safety precautions should always be followed including the following:

1. Do not use outdoors.
2. Do not use this equipment for other than the intended use.
3. Servicing of this equipment should be by qualified personnel only.
4. Do not mount near gas or electric heaters.
5. Use on 120 volt circuits only.

**INSTALLATION INSTRUCTIONS FOR  
INTERMEDIATE, CANDELABRA OR BAYONET BASES  
LED SCREW-IN EXIT FIXTURE RETROFIT KIT**

1. Remove face(s) of existing exit fixture with red pane(s) and remove existing incandescent lamps.
2. Replace lamps with the proper LED unit (intermediate, candelabra or bayonet type base).
3. Screw in LED unit until they are illuminated (finger tight).
4. ~~Position LED unit so that the widest part of the unit is facing the letters "EXIT"~~  
(Turn counterclockwise until parallel with the fixture face).
5. Replace the exit sign face(s) and red panel(s).

**IMPORTANT:** LED'S must be parallel to the face of the exit fixture to insure proper light distribution.

**CAUTION:**

For use only with six inch single or double-faced, stencil-faced fixtures with white or black interiors.

For use in exit lights with interior enclosure dimensions of 6-1/4"H X 9-1/2"W X 7/8"D minimum and 8-7/8"H X 13-7/16"W X 3-1/4"D maximum, including all obstructions.

Not for use in:

- Exit fixtures with an exit legend larger than 6 inches.
- Exit fixtures employing more than two incandescent lamps larger than 20 watts each.
- Edge-Lite or Fluorescent fixtures.

**CAUTION:**

For use only with six inch single or double-faced, stencil-faced fixtures with white or black interiors.

For use in exit lights with interior enclosure dimensions of 6-1/4"H X 9-1/2"W X 7/8"D minimum and 8-7/8"H X 13-7/16"W X 3-1/4"D maximum, including all obstructions.

**DO NOT REMOVE THIS LABEL UNTIL READY FOR INSTALLATION**

**CAUTION - THIS RETROFIT KIT IS INTENDED FOR USE ONLY WITH SIX INCH, SINGLE OR DOUBLE STENCIL - FACED SIGNS WITH WHITE INTERIORS AND DIMENSIONS BETWEEN 12.25"x7.5"x2.25" AND 11.5"x7.88"x2.5". DO NOT INSTALL IN ANY EXIT SIGN UNLESS THE INFORMATION MATCHES EXACTLY IF INCORRECTLY INSTALLED. THIS PRODUCT MAY NOT COMPLY WITH LOCAL AND NATIONAL CODES WITH REGARD TO A LIFE SAFETY DEVICE (EXIT SIGN) AND MAY ADITIONALLY CREATE A RISK OF FIRE.**

WHEN LAMP ADAPTERS HAVE TO BE USED, PLEASE MOUNT THE INSULATION SLEEVE ONTO THE LAMP BASE BEFORE SCREW IN THE ADAPTER (SEE FIG.)